



HALL EFFECT CURRENT SENSOR
CLOSED LOOP

Product Code	HE050T03	HE100T03	HE200T03	HE300T03
I_{pn} RMS (A)	50	100	200	300
I_p Max (A)	+/- 75	+/- 150	+/- 300	+/- 500
I_{out} @ I_{pn}	25 mA	50 mA	100 mA	150 mA
Supply Voltage (V)	+/- 12...18			
Bandwidth -3 dB (kHz)	DC to 100			
Accuracy %	+/- 0.7			
Linearity %	< 0.1			
Secondary connection	pc terminal screw connector			
Mounting Type	Flange Mount			

I_{pn}: primary nominal current
I_p Max: primary maximum current

I_{out}: Output Current @ I_{pn}

(Last updated on 11/03/2011)